

<div data-bbox="118 165 432 232" data-label="Section-Header"> <h2>2.4G & BT5.2 DUAL MODE wireless air mouse and keyboard</h2> </div> <div data-bbox="212 262 368 293" data-label="Text"> <p>user's manual</p> </div> <div data-bbox="129 309 426 801" data-label="Image"> </div> <div data-bbox="82 853 472 898" data-label="Text"> <p>Thank you for choosing our product ! Please read user' s guide before using for properly using.</p> </div>	<div data-bbox="547 136 786 174" data-label="Section-Header"> <h2>1 PRODUCT DIAGRAM</h2> </div> <div data-bbox="555 208 927 871" data-label="Image"> </div> <div data-bbox="740 900 759 918" data-label="Text"> <p>01</p> </div>	<div data-bbox="1008 136 1374 192" data-label="Section-Header"> <h2>THANK YOU FOR USING OUR PRODUCTS EVER SINCE!</h2> </div> <div data-bbox="1008 199 1396 495" data-label="Text"> <p>This is a wireless fidelity air mouse with built-in gyroscope and gravity acceleration sensor; it can perform the functions of a traditional remote control, computer mouse, and gaming motion controller on android platform.</p> <p>Plug and play micro receiver is compatible with personal computer, projector, TV box, Home Theater Personal Computer etc</p> <p>Holding air mouse and rotating your wrist is converted into a movement of a cursor across the screen and it allows you to control your computer; projector and other entertainment equipment from a distance.</p> <p>Ergonomics of air mouse will replace stationary computer mouse and infrared button remote control giving you convenience to manage your computer and television set from a position which is most comfortable for you.</p> </div> <div data-bbox="1008 506 1230 539" data-label="Section-Header"> <h2>2 PRODUCT FEATURES</h2> </div> <div data-bbox="1008 555 1337 889" data-label="Text"> <p>Dual Mode:2.4G & BT5.2</p> <p>Built in 6-axis gyroscope</p> <p>Fully QWERTY mini Keyboard on the backside</p> <p>Built in 250mAh rechargeable lithium battery</p> <p>CPIAdjustment</p> <p>CPI(Count Per Inch), Speed of the Mouse Cursor Adjustment (3 Levels), 1, 2, 3, 4 Level. The higher the level, the faster the speed. The default speed is set at level 2</p> <p>1.Speed Increase: Press[OK] button +[Volume +] button for about 3 seconds, the work indicator flashes quickly and then goes off, release the button,CPI on the basis of the original increase 1 level.</p> <p>2.Speed Decrease: Press [OK] + [Volume -] for about 3 seconds, the work indicator flashes quickly and then goes off, release the button, and CPI is reduced by 1 level on the basis of the original.</p> </div> <div data-bbox="1214 900 1233 918" data-label="Text"> <p>02</p> </div>
<div data-bbox="82 1014 387 1104" data-label="List-Group"> <ul style="list-style-type: none"> [Fn] : Switch to the red character function and the Fn indicator lights up.Press again to switch back to the default function,the Fnindicator goes out. [COM] : Quickly enter www . and . com characters </div> <div data-bbox="82 1137 327 1171" data-label="Section-Header"> <h2>3 PRODUCT SPECIFICATION</h2> </div> <div data-bbox="82 1191 347 1408" data-label="Text"> <p>Transmission Method:2.4G RF wireless & BLE 5.2</p> <p>Sensors:6-axis Gyroscope</p> <p>Number of keys: 58keys</p> <p>Transmission Distance:8-10m</p> <p>Working Current:<5mA</p> <p>Quiescent Current:<15uA</p> <p>Product Material:ABS Plastic and silicone</p> <p>Product Size:155*45*8mm</p> <p>Product Weight:65g</p> </div> <div data-bbox="82 1449 244 1489" data-label="Section-Header"> <h2>4 HOW TO USE</h2> </div> <div data-bbox="82 1512 185 1538" data-label="Section-Header"> <h3>2.4G MODE</h3> </div> <div data-bbox="82 1547 489 1713" data-label="Text"> <p>For initial use, plug a USB receiver into the USB port of device and wait for 20-60 seconds to install driver of USB receiver. Move the mouse, the mouse cursor can move on the screen means that pairing is successful.</p> <p>If it is unsuccessful, press and hold [OK] and [BACK] buttons, LED light begin to flash. Pairing is successful when LED light stop flashing.</p> </div> <div data-bbox="279 1774 298 1792" data-label="Text"> <p>03</p> </div>	<div data-bbox="542 1014 660 1043" data-label="Section-Header"> <h3>BT 5.0 MODE</h3> </div> <div data-bbox="542 1072 948 1655" data-label="List-Group"> <ol style="list-style-type: none"> Before using this device, first you must turn on the BT function of the main device. Then long press"OK"+"Return" keys, when the LED turns to flash quickly, the product enters the pre pairing. Click 'add search new devices" on the main device to find this air remote's name (Example: M5). Click the name can to connecting. After the product is successfully connected, the direction of the mouse pointer can be controlled by waving in the air. If the connection is not successful, please perform the operation steps of item 2-4 again. Reconnect efficiency description: The normal reconnect time of this product is 3-5 seconds after it is normally paired with the main equipment. This product can only remember the pairing information of one main device, when the product is connected to a new device, the connection of historical devices is not supported after. in this case, you need to delete the historical connection information of this peripheral can be successfully matched for new search. </div> <div data-bbox="740 1774 759 1792" data-label="Text"> <p>04</p> </div>	<div data-bbox="1026 1028 1366 1173" data-label="Image"> </div> <div data-bbox="995 1200 1184 1240" data-label="Section-Header"> <h2>5 RED INDICATOR</h2> </div> <div data-bbox="995 1263 1404 1406" data-label="List-Group"> <ol style="list-style-type: none"> When the product is being charged the LED indicator turns red and turns off when fully charged. When the battery is low the LED indicator flashes red at a frequency of 2Hz, in this case charge the device. (When the battery is low the device automatically goes into sleeping mode every 20 seconds) </div> <div data-bbox="995 1422 1163 1464" data-label="Section-Header"> <h2>6 Backlight</h2> </div> <div data-bbox="995 1480 1275 1503" data-label="List-Group"> <ol style="list-style-type: none"> Press(Fn+Space)Can Switch Backlight Color </div> <div data-bbox="995 1529 1090 1570" data-label="Section-Header"> <h2>7 NOTE</h2> </div> <div data-bbox="995 1585 1409 1666" data-label="List-Group"> <ol style="list-style-type: none"> Air mouse functions: Some multi-media device maybe is not available for air mouse, so if the key [OK] doesn't work during device working, please end close air mouse pointer and try again. </div> <div data-bbox="1214 1774 1233 1792" data-label="Text"> <p>05</p> </div>

80G的书纸, 黑白打样品